

## Materials needed

1"x8"x8'

1/4"x7 1/4"x6'

1/4"x24"x24"

3-keyless light fixtures

3- cords

1- outlet strip

Primer and paint

Cut 2-1"x8"x24". (Top and bottom)

Cut 2-1"x8"x22 1/2" (sides)

Cut 1/4"x3/8" deep dados on top and bottom pieces to create 3 equal spaces

Cut 2- 1/4" x 7 1/4" x 23 1/4" ( slide into dados after putting top, bottom and sides together)

Cut 1- 1"x7 1/4" x24" ( front top piece)

Assemble box by laying out the top and bottom (24") and nailing or screwing through the pieces into the sides(22 1/2") at the ends

Nail the back 1/4" x24" x24" this will square up the box

Slide the dividers 2- 1/4" x7 1/4" x 23 1/4" into the dados add a little glue to secure

Nail the front top piece 1"x7 1/4" x24" to the box

Once the glue dries on the dividers sand and paint the box

Drill 1/2" hole in each compartment for the cord to connect the keyless fixture

Mount the outlet strip to the top of the box

Put the desired bulbs in the fixtures and plug it in. DONE

